



Knowledgebase > TRACE32 PowerView > Error message: "FATAL ERROR from InterCom-driver: can not bind read socket"

Error message: "FATAL ERROR from InterCom-driver: can not bind read socket"

2023-06-29 - Comments (2) - TRACE32 PowerView

You are using **InterCom** communication for TRACE32 on your PC. This was activated by a setting in the active configuration for your TRACE32 PowerView software. Either by the **InterCom** setting in the [T32Start](#) configuration or inside your TRACE32 config file (default name config.t32).

The **InterCom** communication is typically needed if two or more TRACE32 PowerView instances shall communicate together (via UDP). This is for example needed for multicore debugging or debugging coprocessors like GTM.

The problem is caused by using the same **InterCom** port address by different applications (several TRACE32 executables or other applications). You can check the used ports by command: "netstat -a" on your PC.

For TRACE32, you can avoid this problem in the configuration of T32Start using the option "Use Auto Increment Port: Yes". If using a config file like config.t32 you need to set a different **InterCom** Port manually.

Tags

InterCom

Comments (2)

Comments (2)

KS **KEILY SUN**

1 year ago

If using a config file like config.t32, how can I set a different InterCom Port manually? How do I describe it in config.t32?

Khaled Jmal

1 year ago

You can set the intercom port number in the IC=NETASSIST section in the config file.

EXample: IC=NETASSIST PORT=12345 Refer for more information to installation.pdf