

Knowledgebase > FAQs by core architecture > Intel® x86/x64 > What does the error message "Onchip breakpoint modified by target program" mean?


What does the error message "Onchip breakpoint modified by target program" mean?

2025-07-26 - Comments (0) - Intel® x86/x64

The debugger sets onchip breakpoints on Intel® x86/x64 processors using debug registers (DR0, DR1, DR2, DR3, DR7). However, these registers can also be accessed and modified by the target application. If this happens, it may lead to unexpected behavior, such as:

- The execution failing to stop at the intended breakpoint
- The program stopping at an unintended location

When the debugger detects that these registers have been modified by the target code, it displays the error message "Onchip breakpoint modified by target program" in the Break.List window:



Additionally, warning messages in the AREA windows indicate which registers have been altered:

```
Detected MIPI60 Whisker
COHold: Writing MSR_PKG_CST_CONFIG_CONTROL for core 0 = 0x00040007
COHold: Writing MSR_PKG_CST_CONFIG_CONTROL for core 1 = 0x00040007
Waiting for BIOS to do necessary initialisations of the board
Warning: DRO of core 0 was modified by the target program
Warning: DR2 of core 0 was modified by the target program
Warning: DR3 of core 0 was modified by the target program
Warning: DR7 of core 0 was modified by the target program
Warning: DR7 of core 0 was modified by the target program

V

Lil
```

Solution:

To prevent this issue, modify the target application to ensure that these registers are not altered. The command TrOnchip.Set GeneralDetect ON can be used here to stop the target execution each time these registers are modified by the target code.

If modifying the target application is not an option, consider using software breakpoints as

an alternative to onchip breakpoints.